

PA7-USD6

PA7 Option Switch Settings: 1

Supported bill US\$ 1, 5, 10, 20, 50, 100 6bills.

PA7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject US\$ 1	ON											
★	Accept US\$ 1	OFF											
	Reject US\$ 5		ON										
★	Accept US\$ 5		OFF										
	Reject US\$ 10			ON									
★	Accept US\$ 10			OFF									
	Reject US\$ 20				ON								
★	Accept US\$ 20				OFF								
	Reject US\$ 50 & 100					ON							
★	Accept US\$ 50 & 100					OFF							
★	Push Out Stacker Disable						ON						
	Push Out Stacker Enable						OFF						
	Harness Disable							ON					
★	Harness Enable						OFF						
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / US\$ 1									OFF	OFF		
	2 pulses / US\$ 1									ON	OFF		
	4 pulses / US\$ 1									OFF	ON		
	20 pulses / US\$ 1									ON	ON		
★	Pulse Speed	50ms LO / 50ms HI										OFF	OFF
		60ms LO / 300ms HI										ON	OFF
		30ms LO / 50ms HI										OFF	ON
		150ms LO / 150ms HI										ON	ON

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

PA7-USD6(Pulse/ICT104U)

Remove the front cover and the dip-switch is on the CPU board.

PA7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ICT104U Mode		OFF		
	Reserved			ON	
★				OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

PA7 Interface Settings: 2 (ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	ICT104U Mode		OFF		
	Reserved			ON	
★				OFF	
	Reserved				ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	US\$ 1	US\$ 1
BV2	US\$ 5	US\$ 5
BV3	US\$ 10	US\$ 10
BV4	US\$ 20	US\$ 20
BV5	US\$ 50	US\$ 50
BV6	US\$ 100	US\$ 100