

## A6-USD2

### A6 Option Switch Settings:(Pulse)

Supported bill US\$ 1, 5 2bills.

A6 dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8
★ Reject US\$ 1	ON							
★ Accept US\$ 1	OFF							
★ Reject US\$ 5		ON						
★ Accept US\$ 5		OFF						
★ 1 pulse / one dollar			OFF	OFF				
2 pulse / one dollar			ON	OFF				
4 pulse / one dollar			OFF	ON				
20 pulse / one dollar			ON	ON				
★ Pulse Speed	50ms on / 50ms off		OFF		OFF	OFF		
	60ms on / 300ms off		ON		ON	OFF		
	30ms on / 50ms off		OFF		OFF	ON		
	150ms on / 150ms off		ON		ON	ON		
★ Harness disable							ON	
★ Harness enable							OFF	
★ Inhibit Active High								ON
Inhibit Active Low								OFF

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW3~SW8 of the 8-switch DIP are for pulse protocol only.

