

A7/V7 Option Switch Settings

Supported bill Can\$ 5, 10, 20, 3bills.

A7/V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Can\$ 5	ON											
	Accept Can\$ 5	OFF											
★	Reject Can\$ 10		ON										
	Accept Can\$ 10		OFF										
★	Reject Can\$ 20			ON									
	Accept Can\$ 20			OFF									
★	Reserved				ON								
	Reserved				OFF								
★	Reserved					ON							
	Reserved					OFF							
★	Reserved						ON						
	Reserved						OFF						
★	Harness disable							ON					
	Harness enable							OFF					
★	Inhibit Active High								ON				
	Inhibit Active Low								OFF				
★	1 pulse / Can\$ 1									OFF	OFF		
	2 pulses / Can\$ 1									ON	OFF		
	4 pulses / Can\$ 1									OFF	ON		
	20 pulses / Can\$ 1									ON	ON		
★	Pulse Speed	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7/V7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	RS232 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

A7/V7 Interface Settings: 3 (RS232)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON		
★	RS232 Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

V7 Interface Settings: 2 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting

V7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
					ON
★					OFF

★ Manufacture setting