

L70-USD6

L70/P5 DIP SWITCHES SETTING : 1(110/12(V) Pulse/ICT104U/ICT104V/MDB)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / USD 1	OFF	OFF	OFF							
2 Pulse / USD 1	OFF	OFF	ON							
3 Pulse / USD 1	OFF	ON	OFF							
4 Pulse / USD 1	OFF	ON	ON							
5 Pulse / USD 1	ON	OFF	OFF							
10 Pulse / USD 1	ON	OFF	ON							
20 Pulse / USD 1	ON	ON	OFF							
100 Pulse / USD 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept USD 1						ON				
Reject USD 1						OFF				
★ Accept USD 5							ON			
Reject USD 5							OFF			
★ Accept USD 10								ON		
Reject USD 10								OFF		
★ Accept USD 20									ON	
Reject USD 20									OFF	
★ Accept USD 50 & 100										ON
Reject USD 50 & 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.
(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-USD6(110/12(V) Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	USD 1	USD 1	USD 1	USD 1
BV2	USD 5		USD 5	USD 5
BV3	USD 10	USD 5	USD 10	USD 10
BV4	USD 20	USD 10	USD 20	USD 20
BV5	USD 50	USD 20	USD 50	USD 50
BV6	USD 100	USD 50	USD 100	USD 100
BV7		USD 100		

DIP SWITCHES SETTING : 2(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
Pulse Mode		ON	OFF	
ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
★ ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104U Mode		OFF	ON	
MDB Mode		ON	ON	
ICT104V Mode		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting