

## V6E-USD4

### V6E Option Switch Settings: 1 (MDB)

Supported bill US\$ 1, 5, 10, 20 4bills.

V6E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject US\$ 1	ON											
	Accept US\$ 1	OFF											
	Reject US\$ 5		ON										
★	Accept US\$ 5		OFF										
	Reject US\$ 10			ON									
★	Accept US\$ 10			OFF									
	Reject US\$ 20				ON								
★	Accept US\$ 20				OFF								
	Reserved					ON							
★	Reserved					OFF							
	High Acceptance						ON						
★	High Security						OFF						
	Reserved							ON					
★	Reserved							OFF					
	Reserved								ON				
★	Reserved								OFF				
	Reserved									ON			
★	Reserved									OFF			
	Reserved										ON		
★	Reserved										OFF		
	Reserved											ON	
★	Reserved											OFF	
	Reserved												ON
★	Reserved												OFF

★ Manufacture setting

◆ Default setting(Factory configuration has all switches in the OFF position.)

Note : (1) Reset the bill acceptor after setting the dip switch.

## V6E-USD4(MDB)

Remove the front cover and the dip-switch is on the CPU board.

### V6E Interface Settings: 2 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Reserved		ON		
★	MDB Interface		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	MDB
BV1	US\$ 1
BV3	US\$ 5
BV4	US\$ 10
BV5	US\$ 20